

The AiroBlue® Printer Adapter allows printer with USB port to communicate with any Bluetooth® enabled mobile phone, PDA, Notebook Computer, Desktop Computer, digital camera and now you can send files to printer for printing without the need of wires and cables, giving you greater freedom and convenience (up to 100m or 328ft in open area).

You can also hook up with you printer to your office network or home network via a Bluetooth® Access Point and turn your Printer to a network printer in just a second.



FEATURES

- Easy to install, just Plug-&-Play
- Enable wireless internet connection
- Enable wireless printing without any cable
- Hook up to an office network wirelessly
- Receive files for printing from any Bluetooth enabled devices
- Synchronize virtually with any Bluetooth enable device
- Bluetooth v1.2/Class I compliant
- Working radius range 100 meters/328 feet

SPECIFICATIONS

Frequency Range:	2.4 to 2.4835 GHz
Receiving Sensitivity:	-80dBm (typical)
TX Power:	20dBm maximum (Class I)
Range:	>100 meters (line-of-sight)
Power Consumption:	0.7W, 6V
Power Adapter:	Input: AC 100 to 240V, Output: DC 6V at 1A
Operating Channels:	79 Channels of 1MHz BW
Host Interface:	USB Specification 1.1 Compliant
Temperature:	Operating: 0°C to 75°C Storage: -20°C to 90°C
Humidity	Operating: 10% to 90% Storage: 10% to 90%
Dimensions:	88 (L) x 36 (W) x 16 (H) mm
OS Support:	Windows 98SE, ME, 2000 & XP
Certifications:	BQB, CE, FCC, WEEE, RoHS

If you need further questions, please go to visit MICRODIA website, www.microdia.com or send us an email, support@microdia.com.

MICRODIA (USA)
Camden Ave., San Jose, CA 95120, USA

MICRODIA (UK)
Brickhill Drive, Manton Height, Bedford,
MK41 7QH, England

MICRODIA (HONG KONG)
International Sales Office
1371, HITEC, Trademart Drive, Kowloon Bay, Hong Kong
Tel: +852.2801.7813
Fax: +852.2801.7060